

BTCC-03

Multipoint BT carkit

STAY CONNECTED

- Make safe handsfree phone calls
- Connect 2 mobile phones at once
- Easy to use one-touch control
- Use for 12 hours without charging
- Make safe handsfree phone calls while driving your car, with this compact BT carkit. This carkit is easy to use and combines an excellent sound quality with a contemporary design. No complex installation required. Simply attach the MobileBird to the sun visor in your car, switch on the BT on your mobile phone and the carkit is ready to use. The buttons on the carkit allow you to answer a call, redial the last number or to adjust the volume.



Specifications

BT v2.1+ EDR

Operating Frequency Band: 2.4GHz ~ 2.48GHz unlicensed ISM band

RF power class II: working distance is up to 8 m BT profiles: Headset and HandsFree,A2DP,AVRCP Integrated echo cancellation and Noise suppressor Built in speaker and microphone

Battery type: rechargeable lithium-polymer battery 3.7 VDC, 500 mAH

Charging time: up to 3 hours Talk time: up to 12 hours

Standby time: more than 800 hours

Car charger: input DC 12-24 VDC; output 5.0 ± 0.2 VDC up to 1 A; black color

Dimensions: 118 x 47 x 15 mm

Features

- BT carkit with excellent full-duplex sound quality
- Multi-link technology: connect two devices simultaneously
- One-touch button for answering, rejecting and redial calls
- Supports Voice Dialling on voice activation enabled phones
- Up to 12 hours talking time and 30 days of standby time, without charging
- Working distance up to 8 meters

Packaging

Q'ty in crtn, pcs Crtn volume, CUM Crtn weight, kgs Individual package size LxWxH: Carton size LxWxH: Country of origin Barcode Customs code

0.026477 3.54 180x115x52 mm 415x220x290 mm CN 8716309101240 8518300090

24

Package contents

BT Handsfree car kit Car charger + USB cable Sun visor clip User manual

Certificates







System requirements

BT enabled mobile phone